



COM4/DIO Pin Select	JP1
COM4	1-2, 4-5, 7-8, 10-11 On
DIO	2-3, 5-6, 8-9, 11-12 On
COM4/DIO Pin Select	JP2
COM4	1-2, 4-5, 7-8, 10-11 On
DIO	2-3, 5-6, 8-9, 11-12 On
Mini PCIe PCIe/SATA Select	JP3
PCIe	2-3 On
SATA	1-2 On
Clear CMOS Data	JP4
Normal	1-2 On
Clear CMOS Data	2-3 On
eDP Backlight Voltage Select (optional)	JP5
+3V3	1-2 On
+5V	2-3 On
eDP Panel Voltage Select (optional)	JP6
+12V	1-2 On
+5V	3-4 On
+3V3	5-6 On
Auto PWR ON	JP7
Normal	1-2 On
Auto-PWR ON	2-3 On

LVDS Backlight Voltage Select	JP8
+3V3	1-2 On
+5V	2-3 On
LVDS DIMM Control	JP9
DC Mode	1-2 On
PWM Mode	2-3 On
LVDS Panel Voltage Select	JP10
+12V	1-2 On
+5V	3-4 On
+3V3	5-6 On
eDP Invert Voltage Select (optional)	JP12
+12V	1-2 On
+5V	2-3 On

Note:

1. SU251: Single 12V +/-10% DC.
2. SU253: Wide Range 15~36V.
3. JP5, JP6 and JP12 will work when the optional eDP connector is populated on the system board.

Battery Notice



Battery Usage

The lithium ion battery powers the real-time clock and CMOS memory. It is an auxiliary source of power when the main power is shut off.



Safety Measures

- Danger of explosion if battery incorrectly replaced.
- Replace only with the same or equivalent type recommended by the manufacturer.
- Dispose of used batteries according to local ordinance.



Mesure de Sécurité de l'usage de Batterie

Batterie:

- Danger d'explosion si la batterie n'est pas correctement remplacée.
- Remplacez seulement avec le même type ou équivalent recommandé par le fabricant.
- Traitez des batteries usées selon le règlement local.