



PS/2 Keyboard/Mouse Power Select	JP1
+5V (default)	1-2 On
+5V_standby	2-3 On
USB Power Select: 0-1 (JP5), 2-3 (JP8), 4-5 (JP6), 10-11 (JP13)	
+5V (default)	1-2 On
+5V_standby	2-3 On
Clear CMOS data	JP9
Normal (default)	1-2 On
Clear CMOS Data	2-3 On
LCD/Inverter Power Select	JP2
+12V	1-2 On
+5V (default)	2-3 On
Panel Power Select	JP11
+12V	1-2 On
+5V	3-4 On
+3.3V (default)	5-6 On
Switch 1	1 On 1 Off 2 On 2 Off
LVDS Channel and bpp Select	Single LVDS Dual LVDS VESA (24bpp) JEIDA or VESA (18bpp)

Power-on Select	JP10
Power-on via power button (default)	1-2 On
Power-on via AC power	2-3 On
Mini PCIe Signal Select	JP12
PCIe (default)	1-4-7-10 2-5-8-11 On
mSATA	2-5-8-11 3-6-9-12 On
Digital I/O Power Select	JP15
+5V_standby (default)	1-2 On
+5V	2-3 On
Digital I/O Output State: DIO 0-3 (JP16), DIO 4-7 (JP17)	
+5V or +5V_standby (default)	1-2 On
GND	2-3 On

Battery Notice



Battery Usage

The lithium ion battery powers the real-time clock and CMOS memory. It is an auxiliary source of power when the main power is shut off.



Safety Measures

- Danger of explosion if battery incorrectly replaced.
- Replace only with the same or equivalent type recommend by the manufacturer.
- Dispose of used batteries according to local ordinance.



Mesure de Sécurité de l'usage de Batterie

Batterie:

- Danger d'explosion si la batterie n'est pas correctement remplacée.
- Remplacez seulement avec le même type ou équivalent recommandé par le fabricant.
- Traitez des batteries usées selon le règlement local.